

SHUNT FED LOW BAND ANTENNAS

A1801H-27	
FREQ (MHz)	CUT WHIP
26	49"
27	48"
28	45"
29	43"
30	39"
31	38"

A1801H-30	
FREQ (MHz)	CUT WHIP
30	49"
31	45"
32	42"
42	39"
34	36"
35	35"

A1801H-34	
FREQ (MHz)	CUT WHIP
32	49"
33	46"
34	43"
35	41"
36	38"
37	36"

A1801H-37	
FREQ (MHz)	CUT WHIP
36	49"
37	47"
38	46"
39	44"
40	42"

A1801H-39	
FREQ (MHz)	CUT WHIP
39	49"
40	48"
41	46"
42	44"
43	42"
44	40"
45	42"

A1801H-45	
FREQ (MHz)	CUT WHIP
45	42"
46	41"
47	39"
48	38"
49	37"
50	35"
51	34"
52	33"
53	32"
54	31"

A1801H-47	
FREQ (MHz)	CUT WHIP
47	49"
48	48"
49	46"
50	45"
51	44"
52	42"
53	41"
54	40"

A18H31 Dual Band	
144-148 /50-54	45"

*When cutting a whip that will be used with the standard Comtelco shock spring, the length of the cut should be reduced by 2".